



AKURATE CD PLAYER

OVERVIEW

CD / SACD / DVD-Audio player

KEY FEATURES INCLUDE

- Plays CD, Super Audio CD and DVD-Audio recordings in stereo or surround sound
- Linn's proprietary audio-optimised 'silent power' Switch Mode Power Supply
- Linn's proprietary adaptive Silver Disk Engine™ technology
- High-quality metal drawer mechanism
- Available in black or silver finish



1

Designed for music lovers, the Akurate CD player is designed to extract the most music from high quality audio disc formats.

It is optimised for exceptional sound quality from stereo music, and can also be configured for multi-channel music to enjoy higher quality SACD and DVD-Audio recordings in surround sound.

The player can play the stereo or multi-channel layer on an SACD disc, and display artist, title and track information on the front panel.

Linn's Silver Disk Engine™ technology identifies the disc type and reconfigures the system for the highest performance level available, unlike multi-format players which convert the signal to a single format and play back at a standard performance level. This means that the Akurate CD player plays the highest quality music formats at their maximum potential.

The Akurate CD player can be integrated with a Linn Knekt multi-room audio system.

Available in black or silver finish, the Akurate CD player complements other components in the Akurate System.



2

AKURATE CD PLAYER

TECHNICAL SPECIFICATION

CD / SACD / DVD-Audio player

■	Date of Introduction	May 2007
■	Type	CD / DVD-Audio / SACD player
■	Size	(H) 80 mm x (W) 381 mm x (D) 360 mm (H) 3.1 inches x (W) 15 inches x (D) 14.2 inches
■	Weight	4.5 kg 10 lbs
■	Supported Disc Types	CD, SACD (Super Audio CD), DVD-Audio, DTS Audio CD, CD-R, CD-RW
■	Audio Decoding	PCM streams for simultaneous analogue/digital stereo output, DSD (from SACD), MLP and LPCM (from DVD-Audio) for analogue only output (max 6 channels)
■	Analogue Audio Outputs	5.1 Phono socket outputs (Front L and Front R are double connectors) Stereo XLR Balanced Audio outputs
■	Digital Audio Outputs	SPDIF BNC Output TOSLINK Output
■	Control	RC5 In & Out (KNEKT) RS232 In & Out (RS232 & Flash Upload) Front panel 6 button interface Luminous remote control handset 128 x 32 Front Panel Display Front panel display menu for set-up
■	Power Supply	Switching power supply with auto-ranging (AC 100 - 120 V @ 50 - 60 Hz) (AC 220 - 240 V @ 50 - 60 Hz)

The above information is subject to change without prior notice.

Linn Products Limited
Glasgow Road, Waterfoot, Eaglesham, Glasgow G76 0EQ, Scotland, UK.
Telephone: +44 (0) 141 307 7777, Facsimile: +44 (0) 141 644 4262, Helpline: 0500 888909, E-mail: helpline@linn.co.uk, Website: www.linn.co.uk

Linn Products Inc
8787 Perimeter Park Boulevard, Jacksonville FL 32216, USA.
Telephone: +1 (904) 645 5242, Facsimile: +1 (904) 645 7275, Helpline: 888-671-LINN, E-mail: helpline@linninc.com, Website: www.linninc.com

Linn Deutschland GmbH
Hühnerposten 1d, 20097 Hamburg, Deutschland.
Telephone: +49 (0) 40 890 660 0, Facsimile: +49 (0) 40 890 660 29, E-mail: info@linngmbh.de, Website: www.linn.co.uk

Linn Records Limited
Glasgow Road, Waterfoot, Eaglesham, Glasgow G76 0EQ, Scotland, UK.
Telephone: +44 (0) 141 303 5027/5029, Facsimile: +44 (0) 141 303 5007, E-mail: info@linnrecords.co.uk, Website: www.linnrecords.com

Copyright © 2007, Linn Products Limited. All rights reserved.

Linn, the Linn logo and all other Linn product names and slogans are trade marks or registered trade marks of Linn Products Limited, registered in at least the UK and/or the EU. Linn Products Limited disclaims any proprietary interest in trade marks and trade names other than its own.

PACK 1330 (05/07)